

choisir le ballast-l'amorçeur_lampe philips

lampes	Appareillages ferro magnétiques					Ballasts électroniques					
	ballast	tension Réseau	Amorçeur	Condensateur	ballast	ballast					
MASTER CosmoPolis					Fix Output		DV Xtreme Prog (DALI,ALO,CLO, AMPDIM,DYNADIMMER)				
MASTER CPO-TW/TT 45W					HID-PV Xt 45 CPO Q	668961 00	HID-DV Prog Xt 45 CPO C	212102 00			
							HID-DV PROG Xt 45 CPO Q	669142 00			
MASTER CPO-TW/TT 60W					HID-PV Xt 60 CPO Q	241430 00	HID-DV Prog Xt 60 CPO C	204534 00			
							HID-DV PROG Xt 60 CPO Q	241492 00			
MASTER CPO-TW/TT 90W					HID-PV Xt 90 CPO Q	241454 00	HID-DV Prog Xt 90 CPO C	204558 00			
							HID-DV PROG Xt 90 CPO Q	241515 00			
MASTER CPO-TW/TT 140W					HID-PV Xt 140 CPO Q	241478 00	HID-DV Prog Xt 140 CPO C	204572 00			
							HID-DV PROG Xt 140 CPO Q	241539 00			
Sodium haute pression SON(-T)					Fix Output Xtreme						
SON-T I 50W	BSN 50/70 K407-ITS	886931 00	230/240	intégré à la lampe	10µF/250V						
	BSN 50/70 K407-TS	940473 00	230/240								
SON-T I 70W	BSN 70 L33 TS	059680 31	230		12µF/250V						
	BSN 70 L34 TS	059703 31	240								
	BSN 70 K407-ITS	886948 00	230/240								
	BSN 50/70 K407-TS	940473 00	230/240								
	BSN 70/100 K407-TS	940534 00	230/240								
SON-T E 50W	BSN 50 L33-TS	748225 30	230		SND 57	930668 30	10µF/250V	HID-PV Q Xt SON50	698760 00		
	BSN 50 K407-ITS	886931 00	230/240		SKD 578	895674 00		HID-PV Base 50 SON C3	531471 00	HID-DV PROG Xt 50 SON Q	669241 00
	BSN 50/70 K407-TS	940473 00	230/240		SUD 10-S	931443 30					
				220-240V 50/60Hz							
SON-T E 70W	BSN 70 L33 TS	059680 31	230	SND 57	930668 30	12µF/250V	HID-PV Q Xt SON70	698784 00			
	BSN 70 L34 TS	059703 31	240	SKD 578	895674 00		HID-DV PROG Xt 70 SON Q				
	BSN 70 K407-ITS	886948 00	230/240	SUD 10-S	931443 30			HID-PV Base 70 SON C3	531518 00	669265 00	
	BSN 50/70 K407-TS	940473 00	230/240	220-240V 50/60Hz							
SON(-T) 100W	BSN 100 L33 TS	059727 31	230	SND 58	930682 30	12µF/250V		HID-PV Q Xt SON100	698807 00		
	BSN 100 L34 TS	059741 31	240	SKD 578	895674 00		HID-DV PROG Xt 100 SON Q				
	BSN 100 K407-ITS	886955 00	230/240	SUD 40-S	930354 30			HID-PV Base 100 SON Q	531556 00	669289 00	
	BSN 70/100 K407-TS	940534 00	230/240								
	BSN 100/150 K407-TS	940688 00	230/240								
SON(-T) 150W	BSN 150 L33 TS	059604 30	230	SND 58	930682 30	18µF/250V	HID-PV Q Xt SON150	698821 00			
	BSN 150 L34 TS	059628 30	240	SKD 578	895674 00		HID-DV PROG Xt 150 SON Q				
	BSN 150 K407-ITS	886986 00	230/240	SUD 40-S	930354 30			HID-PV Base 150 SON Q	531570 00	669302 00	
	BSN 100/150 K407-TS	940688 00	230/240								
	BSN 150/250 K407-TS	940923 00	230/240								
SON(-T) 250W	BSN 250 L33 TS	059642 30	230	SND 58	930682 30	32µF/250V	HID-PV Xt 250 SON	222712 00	HID-DV PROG Xt 250 SON C2	219910 00	
	BSN 250 L34 TS	059666 30	240	SKD 578	895674 00						
	BSN 250 K407-ITS	887020 00	230/240	SUD 40-S	930354 30						
	BSN 150/250 K407-TS	940923 00	230/240								
	BSN 250/400 K407-TS	940862 00	230/240								
SON(-T) 400W	BSN 400 L33 TS	059765 30	230	SND 58	930682 30	45µF/250V					
	BSN 400 L34 TS	059789 30	240	SKD 578	895674 00						
	BSN 400 K407-ITS	887044 00	230/240	SUD 40-S	930354 30						
	BSN 250/400 K407-TS	940862 00	230/240								
SON(-T) 1000W	BSN 1000 L78	062369 00	230/240	SN 61	916396 30	100µF/250V					

choisir le ballast-l'amorçeur_lampe philips

lampes	Appareillages ferro magnétiques					Ballasts électroniques	
	ballast	tension Réseau	Amorçeur	Condensateur	ballast	ballast	
Sodium basse pression SOX / SOX-						Fix Output	
MASTER SOX-E 18W							
MASTER SOX PSG et SOX 35W						EXC 035 S/50	062383 30
MASTER SOX-E 36W						EXC 036 S50	062406 30
MASTER SOX PSG et SOX 55W	BSX 55 H26	919960 30	220/230	SX 72	915610 30	5,7µF/450V	
MASTER SOX-E / PSG 66W	BSX 90 L40	919939 31	230	SX 76	916402 30	10µF/230V	
SOX 90W	BSX 90 L40	919939 31	230	SX 76	916402 30	10µF/230V	
MASTER SOX-E 91W	BSX 91 H96	920393 30	220/240	SX 74	915696 30	5,2µF/300V	EXC 091 S50
MASTER SOX-E 131W	BSX 131 H96	919786 30	220/240	SX 131	915894 30	3,4µF/650V	
SOX 135W	BSX 135 H96	920072 30	220/240	SX 74	915696 30	6,8µF/420V	
SOX 180W	BSX 180 H96	939005 30	220/240	SX 73	920058 30	4,4µF/650V	
Vapeur de mercure HPL-N							
HPL-N 50w E27	BHL 50/80 K407	940077 00	230/240				
HPL-N 80W E27	BHL 50/80 L407	919670 31	230/240			8µF/250V	
	BHL 50/80 K407	940077 00	230/240				
HPL-N 125W E27	BHL 80/125 K407	940138 00	230/240			10µF/250V	
	BHL 125 L40	915146 31	230				
	BHL 125 L32	919441 31	240				
HPL-N 250W E40	BHL 80/125 K407	940138 00	230/240			18µF/250V	
	BHL 250 L40	919502 30	230				
	BHL 250 L32	944894 30	240				
HPL-N 400W E40	BHL 250 K307	887013 00	230/240			25µF/250V	
	BHL 400 L40	919533 30	230				
HPL-N 1000W E40	BHL 400 K307	887037 00	230/240				
	BHL 1000 L78	062376 00	230/240				

source document : [Catalogue Lampes et appareillage conventionels \(mise à jour 2017\) page 77 \(149\).pdf](#)

https://images.philips.com/is/content/PhilipsConsumer/PDFDownloads/France/ODLI20170511_001-UPD-fr_FR-Catalogue_Lampes_2017.pdf#page=77